Received: 10/28/2004 Status: CANCELLED Effective Date: 03/01/2005

PSC NO.: 2 ELECTRICITY LEAF: 6 COMPANY: ILION BOARD OF LIGHT COMMISSIONERS REVISION: 0 INITIAL EFFECTIVE DATE: 3/1/2005 SUPERSEDING REVISION:

SERVICE CLASSIFICATION NO. 1 (CONT'D)

SPECIAL PROVISIONS (CONT'D):

- E. The Utility will furnish the meter base, size not to exceed 200 amperes, for single and duplex residences. The Customer shall be responsible for the installation of same at a Utility specified location. Residential installations for single and duplex residences requiring larger than a 200 ampere meter base per location shall bear a charge for the differential in cost between the standard 200 ampere meter base and the larger size requested by the Customer and shall be supplied by the Utility for the Customer's installation of same. All meters shall be furnished and installed by the Utility.
- F. The Utility will furnish single phase meter bases, at the Utility's expense, up to a six (6) position meter location and the Customer shall be responsible for the installation of same. All meters shall be furnished and installed by the Utility.
- G. For apartmental installations in excess of six (6) single phase meter positions or one (1) three phase meter position (network metering), the Customer shall furnish and install a modular meter cabinet installation of the required number of meter positions, internally prewired with busbars of the required capacity and supplied with a lockable disconnect means for each meter position. The character of service (voltages) for service to apartmental units shall be 120/240 volt single phase or 120/208 volt, three phase, four wire, Wye at the Utility's option based on availability, loadings, etc. All meters shall be furnished and installed by the Utility. For installations in excess of six (6) metered positions, the Customer shall install the meter module within the structure and shall be accessible to Utility personnel on a round-the-clock basis. Location of meter modules will not be accepted if location is to be utilized as any form of storage facility. Total access to the meter module must be guaranteed by the Customer.
- H. The Customer shall apply for and receive permission from the Utility prior to effecting any changes and/or modification of the Customer's wiring or service. Failure to comply with this regulation shall cause the Utility to refuse its service to, or remove its service from, any installation which in the judgment of the Utility will injuriously affect the operation of its system or its service to others.

Issued by: Kevin J. Manfreda, Superintendent, Municipal Building, Ilion, NY 13357